



VLT® 2800 Series



The VLT® 2800 series has been developed for the low power market. The drive is extremely compact and prepared for side-by-side mounting. The concept is modular with a power module and a control module.

The VLT® 2800 series is designed for stable operation in industrial environments.

The perfect solution for:

- Conveyors, centrifuges, dosing pumps, compressors
- Special applications like cutting machines with constant speed, and packaging machines with a need for high precision

Power range:

1/3 x 200 – 240 V: 0.37 – 3.7 kW
 3 x 380 – 480 V: 0.55 – 18.5 kW

With 160% overload torque (normal overload)

Features	Benefits
• Automatic Motor Tuning	• Ensure optimal match between drive and motor
• PID-controller	• Increasing performance
• Interrupt start/stop	• Optimum process control
• Dry run detection	• High repeatability of positional accuracy
• Fieldbus communication	• No need for specific detection equipment
	• Allows for control and surveillance of the drives from a PC or a PLC
	• Profibus and DeviceNet are available
Reliable	Maximum up-time
• Built-in RFI filter	• Compliance with the EMC standard EN 55011 1A
• Enhanced sleep mode	• Excellent control for shutting down the pump at low flow
• Max. ambient temperature 45° Celsius without derating	• No external cooling or oversizing necessary
User-friendly	Save commissioning and operating cost
• Quick Menu	• Easy to use
• Pipe Fill mode	• Prevents water hammering
• Fieldbus communication	• Allows for control and surveillance of the drives from a PC or a PLC
	• Profibus and DeviceNet are available

PC software tools

- **MCT 10**
 - Ideal for commissioning and servicing the drive
- **MCT 31**
 - Harmonics calculations tool

RFI filter

The RFI filter ensures that the frequency converter will not disrupt other electrical components that are connected to the mains and might cause operating disruption.

By fitting an RFI 1B filter module between the mains supply and the VLT® 2800, the solution complies with the EMC norm EN 55011-1B.

Mains	Type	Power		Input current	
		$P_{N,M}$ [kW]	I_{INV} [A]	$I_{L,N}$ [A]	
1 x 220 – 240 V	2803	0.37	2.2	5.9	
	2805	0.55	3.2	8.3	
	2807	0.75	4.2	10.6	
	2811	1.1	6.0	14.5	
	2815	1.5	6.8	15.2	
	2822*	2.2	9.6	22.0	
	2840*	3.7	16.0	31.0	
3 x 200 – 240 V	2803	0.37	2.2	2.9	
	2805	0.55	3.2	4.0	
	2807	0.75	4.2	5.1	
	2811	1.1	6.0	7.0	
	2815	1.5	6.8	7.6	
	2822	2.2	9.6	8.8	
	2840	3.7	16.0	14.7	
3 x 380 – 480 V	2805	0.55	1.7	1.6	
	2807	0.75	2.1	1.9	
	2811	1.1	3.0	2.6	
	2815	1.5	3.7	3.2	
	2822	2.2	5.2	4.7	
	2830	3.0	7.0	6.1	
	2840	4.0	9.1	8.1	
	2855	5.5	12	10.6	
	2875	7.5	16	14.9	
	2880	11.0	24	24.0	
2881	15.0	32	32.0		
2882	18.5	37.5	37.5		

* Not available with RFI filter

Specifications

Mains supply (L1, L2, L3)	
Supply voltage	200 – 240 V ±10%, 380 – 480 V ±10%
Supply frequency	50/60 Hz
Displacement Power Factor (cos φ) near unity	(> 0.98)
Switching on input supply L1, L2, L3	1 – 2 times/min.
Output data (U, V, W)	
Output voltage	0 – 100% of supply
Switching on output	Unlimited
Ramp times	1 – 3600 sec.
Closed loop	0 – 132 Hz
Digital inputs	
For start/stop, reset, thermistor, etc.	5
Logic	PNP or NPN
Voltage level	0 – 24 VDC
Digital outputs	
No. of digital outputs	1
Analogue inputs	
No. of analogue inputs	2
Voltage level	-10 to +10 V (scaleable)
Current level	0/4 to 20 mA (scaleable)
Pulse inputs	
No. of pulse inputs	2
Voltage level	0 – 24 VDC (PNP positive logic)
Pulse input accuracy	(0.1 – 110 kHz)
Analogue outputs	
Programmable analogue outputs	1
Current range at analogue output	0/4 – 20 mA
Relay outputs	
No. of relay outputs	1
Fieldbus communication	
RS485	
Ambient temperature	
45°C	

Cabinet sizes [mm]

Height

	A	B	C	D
A:	200	267.5	267.5	505
a:	191	257	257	490

Width

	B	C	D
B:	75	90	140
b:	60	70	120

Depth

	C	D
C:	168	244

